

RDM7-100 Series

Application



RDM7-100(NC, DZ47-100) series circuit breaker is good shape, light weight, reliable performance, high breaking capacity, quick tripping, rail installation and long life span. It is mainly used in AC 50Hz/60Hz single-pole 230V, two poles, three poles and four poles 400V for overload and short-circuit protection and also can be used for infrequent switch on-off the device and lighting under normal conditions.

The product meets the standards of GB14048.2 and IEC60947-2.

Model

RD M 7 - 100 / □

↓ ↓ ↓ ↓ ↓

① ② ③ ④ ⑤

①	Company Code
②	Miniature Circuit Breaker
③	Design Number
④	Frame Class Rated Current
⑤	Number of Pole

Main Technical Parameters



Number of Pole	1, 2, 3, 4
Rated Frequency (Hz)	50, 60
Frame Class Rated Current (A)	100
Rated Voltage (V)	230/400
Rated Current (A)	63, 80, 100
Rated Breaking Capacity (KA)	10

Overall And Mounting Dimensions (mm)

